



MULTIPLEX ADAPTER ALIGNMENT USING FM STEREO GENERATOR AND AUDIO GENERATOR

	SIGNAL GENERATOR	CONNECT SCORE	ADJUST	REMARKS
1	18KC to MPX Input .	Vert Amp to Point (C) low side to chassis.	A1	Adjust for Maximum .
2	18KC to MPX Input.	Vert Amp to Point (C) low side to chassis.	A2	Adjust for Maximum, set scope to lock 2 cycle waveform.
3	18KC to MPX Input.	Vert Amp to point (C) low side to chassis.	A3	Adjust for Maximum deflection of 4 cycle waveform.
4	67KC to MPX Input.	Vert Amp to point (C) low side to chassis.	A4, A5	Adjust for MINIMUM
5	19KC to MPX Input .	Vert Amp to point (C) low side to chassis.	A6	Adjust for maximum .

