



#### MULTIPLEX ALIGNMENT USING FM STEREO GENERATOR

|    | SIGNAL GENERATOR         | CONNECT SCOPE                                   | ADJUST | REMARKS  |
|----|--------------------------|---|--------|--|
| 1. | 19KC to Multiplex Input. | Vert. amp. to Pin 7 of V1, low side to chassis. | A1     | Adjust for maximum deflection.   |
| 2. | "                        | Vert. amp. to pin 7 of V2, low side to chassis. | A2, A3 | "  |
| 3. | "                        | Vert. amp. to point X, low side to chassis.     | A4, A5 | "  |
| 4. | "                        | Vert. amp. to pin 1 of V4, low side to chassis. | A6     | "  |
| 5. | "                        | Vert. amp. to pin 2 of V4, low side to chassis. | A7     | Adjust for maximum deflection. Retouch A6, A7 to obtain maximum equal deflection if necessary. |

